C2033 (BK)

14401

Power point (19N236)



F03199

Pin	Circuit	Circuit function
1	1049 (BN/PK)	Voltage supplied at all times (overload protected)
2	–	not used
3	57 (BK)	Ground

C2035 (BU)

14401

Parking aid disable switch (15A860)



F08060

Pin	Circuit	Circuit function
1	57 (BK)	Ground
2	1435 (DG/VT)	On/Off signal
3	–	not used
4	57 (BK)	Ground
5	–	not used
6	1436 (VT/OG)	On/Off signal, Light emitting diode (LED), control
7	–	not used
8	19 (LB/RD)	Instrument illumination, feed

C2039

19B107

Hazard flasher switch



F08060

Pin	Circuit	Circuit function
1	385 (WH/RD)	Electronic flasher module
2	57 (BK)	Ground
3	–	not used
4	57 (BK)	Ground
5	–	not used
6	–	not used
7	–	not used
8	19 (LB/RD)	Instrument illumination, feed