C1001

14290

Wiper high/low relay



F05129

Pin	Circuit	Circuit function
30	61 (YE/RD)	Wiper motor relay, high/low, input
85	65 (DG)	Voltage in Run or Accessory (overload protected)
86	647 (GY/LB)	Wiper high/low relay, control
87	58 (WH)	Wiper high/low relay, switched power, output, High
87A	56 (DB/OG)	Wiper high/low relay, switched power, output, Low

C1002

14290

Wiper run/park relay



F05110

Pin	Circuit	Circuit function
1	646 (YE/WH)	Wiper run/park relay, control
2	65 (DG)	Voltage in Run or Accessory (overload protected)
3	61 (YE/RD)	Wiper motor relay, high/low, input
4	28 (BK/PK)	Windshield wiper motor (17508), position, signal
5	65 (DG)	Voltage in Run or Accessory (overload protected)

C1007

14290

Fog lamp relay



F05129

Pin	Circuit	Circuit function
30	477 (LB/BK)	Voltage supplied at all times (overload protected)
85	275 (YE)	Fog lamp relay, control
86	188 (WH/BK)	Fog lamp switch, output
87	478 (TN/OG)	Fog lamp relay, output
87A	–	not used

* 3.8L

C1010 (BK)

12A581



F08052

***9D930/12B637**



F08050

(1) 1145 (LB/BK)
(2) 1087 (OG)
(3) 389 (WH/BK)
(4) 390 (TN/YE)
(5) 393 (VT/LG)
(6) 392 (RD/LG)
(7) 1144 (YE/BK)
(8) 1143 (WH/BK)