C1056

14290

K305
High speed fan control relay



F05074

Pin	Circuit	Circuit function
1	1153 (RD/BK)	Voltage supplied at all times (overload protected)
2	638 (OG/LB)	High speed cooling fan relay, control
3	68 (OG/BK)	Air filter sensor
5	639 (LG/VT)	High speed cooling fan relay, control
6	–	not used

C1058

14290

K309
Low speed fan control relay



F05129

Pin	Circuit	Circuit function
30	1155 (YE/BK)	Voltage supplied at all times (overload protected)
85	229 (RD/OG)	Low speed fan control relay, switched power
86	68 (OG/BK)	Air filter sensor
87	228 (DB)	Voltage supplied at all times (overload protected)
87A	–	not used

C1066

12B637

Y133
Idle Air Control
(IAC) valve (9F715)



F02103

Pin	Circuit	Circuit function
1	361 (RD)	Voltage supplied in Start and Run (overload protected)
2	264 (WH/LB)	Idle speed control valve, control