C901 (GY)

14334

Rear interior lamp



F03299

Pin	Circuit	Circuit function
1	53 (BK/LB)	Interior lamp relay, switched power, output
2	57 (BK)	Ground
3	54 (LG/YE)	Voltage supplied at all times (overload protected)

C907 (NA)

14335

Vanity mirror lamp, left (04100)



F01051

Pin	Circuit	Circuit function
1	54 (LG/YE)	Voltage supplied at all times (overload protected)

C913 (GY)

14334



F03323

14334



F03157

(1) 53 (BK/LB)
(2) 57 (BK)
(3) 54 (LG/YE)

C906 (NA)

14335

Vanity mirror lamp, right (04100)



F01051

Pin	Circuit	Circuit function
1	54 (LG/YE)	Voltage supplied at all times (overload protected)