C1012

14K733

K5
Daytime Running
Lamps (DRL) relay



F20012

Pin	Circuit	Circuit Function
1	15S-LE6 (GN/YE)	Voltage, ignition switch in Start or Run (not overload protected), switched
2	91-LE6 (BK/YE)	Ground
3	30-LE7 (RD)	Voltage supplied at all times (not overload protected)
4	–	not used
5	15S-LE8 (GN/RD)	Voltage, ignition switch in Start or Run (not overload protected), switched

C1013

14K733

K26
Fog lamp relay



F20012

Pin	Circuit	Circuit Function
1	15S-LD8 (GN/RD)	Voltage, ignition switch in Start or Run (not overload protected), switched
2	91-LD8 (BK/OG)	Ground
3	15S-LD9 (GN/BK)	Voltage, ignition switch in Start or Run (not overload protected), switched
4	–	not used
5	15S-LD1 (GN/YE)	Voltage, ignition switch in Start or Run (not overload protected), switched