Power mirror switch (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Left mirror, Up/Down Circuit	4 and 2	Rest	Open circuit
		Up	Closed circuit
		Down	Open circuit
	2 and 6	Rest	Open circuit
		Up	Open circuit
		Down	Closed circuit
Right mirror, Up/Down Circuit	1 and 4	Rest	Open circuit
		Up	Closed circuit
		Down	Open circuit
	1 and 6	Rest	Open circuit
		Up	Open circuit
		Down	Closed circuit
Left mirror, Left / Right	5 and 4	Rest	Open circuit
		Left	Open circuit
		Right	Closed circuit
	5 and 6	Rest	Open circuit
		Left	Closed circuit
		Right	Open circuit
Right mirror, Left / Right	7 and 4	Rest	Open circuit
		Left	Open circuit
		Right	Closed circuit
	7 and 6	Rest	Open circuit
		Left	Closed circuit
		Right	Open circuit
Up/Down Circuit	4 and 3	Rest	Open circuit
		Up	Open circuit
		Down	Closed circuit
	3 and 6	Rest	Open circuit
		Up	Closed circuit
		Down	Open circuit
Left / Right	4 and 3	Rest	Open circuit
		Left	Closed circuit
		Right	Open circuit
	3 and 6	Rest	Open circuit
		Left	Open circuit
		Right	Closed circuit