C367

14B720

A155
Side air bag module, left



F02215

Pin	Circuit	Circuit Function
1	1258 (RD)	Air bag - driver side impact - to module - return
2	1257 (WH/LB)	Air bag - driver side impact - to module - feed

C375

19A442

P77
In–line fuse



F02213

Pin	Circuit	Circuit Function
1	720 (RD/YE)	Voltage supplied at all times (overload protected)
2	720 (RD/YE)	Voltage supplied at all times (overload protected)

C370

14A012

E39
Ashtray illumination lamp



F02219

Pin	Circuit	Circuit Function
1	1045 (DB/WH)	Illumination dimmer, output
2	57 (BK)	Ground

C380

14A012

N251
Power point



F030163

Pin	Circuit	Circuit Function
1	40 (LB/WH)	Voltage supplied at all times (overload protected)
2	–	not used
3	57 (BK)	Ground