Master window/door lock/unlock switch, Convertible (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Power and Ground Checks Before Any Other Tests	15 and 14	All window switches, all positions	Open circuit
	14 and 8, 6, 7, 9, 10, 12, 11, 13	All window switches, at rest	Closed circuit
	3 and 2, 4	Door lock switch, at rest	Open circuit
Left front window circuit	15 and 8	Up	Closed circuit
	15 and 6	Down	Closed circuit
Right front window circuit	15 and 7	Up	Closed circuit
	15 and 9	Down	Closed circuit
Left rear window circuit	15 and 10	Up	Closed circuit
	15 and 12	Down	Closed circuit
Right rear window circuit	15 and 11	Up	Closed circuit
	15 and 13	Down	Closed circuit
Window lockout	15 and 16	Lock	Open circuit
		Unlock	Closed circuit
Door lock switch	3 and 4	Lock	Closed circuit
	3 and 2	Unlock	Closed circuit