## Power window switch, driver

### Component testing procedure

| Circuit to test | Connect self–powered test light or ohmmeter to terminals | Move switch to these positions | A good switch will indicate |
|---|---|---|---|
| **Power and Ground Checks Before Any Other Tests** | 4 and 1 | All switches, all positions | Closed circuit |
| | 1 and 7 | All switches, at rest | Closed circuit |
| | 1 and 8 | | |
| | 1 and 2 | | |
| | 1 and 3 | | |
| **Left front window circuit** | 4 and 7 | Up | Closed circuit |
| | 4 and 8 | Down | Closed circuit |
| **Right front window circuit** | 4 and 2 | Down | Closed circuit |
| | 4 and 3 | Up | Closed circuit |