C922 (GY)

14334



F04153

1) 705 (LG/OG)
2) 400 (LB/BK)
3) 57 (BK)
4) 53 (BK/LB)

14A005



F04183

C1000

14290

Daytime Running Lamps (DRL) relay



F05064

Pin	Circuit	Circuit function
1	164 (VT/LB)	Daytime Running Lamps (DRL) relay, control
2	1087 (OG)	Voltage in Run (overload protected)
3	13 (RD/BK)	Low beam, Ground
4	–	not used
5	932 (GY/WH)	Daytime Running Lamps (DRL) relay, switched output

C1001

14290

Wiper high/low relay



F05064

Pin	Circuit	Circuit function
1	950 (WH/BK)	Voltage in Run or Accessory (overload protected)
2	647 (GY/LB)	Wiper high/low relay, control
3	61 (YE/RD)	Wiper motor relay, high/low, input
4	58 (WH)	Wiper high/low relay, switched power, output, Low
5	56 (DB/OG)	Wiper high/low relay, switched power, output, High