Master window/door lock/unlock switch – front and rear power windows

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Power and Ground Checks Before Any Other Tests	13 and 16	all positions	Open circuit
Left front window circuit	13 and 15 16 and 8	Up	Closed circuit
	13 and 8 16 and 15	Down	Closed circuit
Right front window circuit	13 and 9 16 and 10	Up	Closed circuit
	13 and 10 16 and 9	Down	Closed circuit
Left rear window circuit	13 and 7 16 and 5	Open	Closed circuit
	13 and 5 16 and 7	closed	Closed circuit
Right rear window circuit	13 and 2 16 and 1	Open	Closed circuit
	13 and 1 16 and 2	closed	Closed circuit