Multifunction switch -6

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Headlamp flasher	6 and 7	Neutral	Open circuit
		Headlamp flasher	Closed circuit
		High beam	Closed circuit
High beam	6 and 7	Neutral	Open circuit
		Headlamp flasher	Closed circuit
		High beam	Closed circuit
High beam	8 and 7	Neutral	Open circuit
		Headlamp flasher	Open circuit
		High beam	Closed circuit
Low beam	8 and 9	Neutral	Closed circuit
		Headlamp flasher	Closed circuit
		High beam	Open circuit
LH turn signal	2 and 1	Neutral	Open circuit
		Flash left (no detent)	Closed circuit
		LH turn signal	Closed circuit
RH turn signal	2 and 3	Neutral	Open circuit
		Flash right (no detent)	Closed circuit
		RH turn signal	Closed circuit
Buzzer	4 and 5		40–50 Ω