C801

* Cartier, long wheelbase

14A511

Window adjust switch, right rear (14A412)



F08074

Pin	Circuit	Circuit function
1	–	not used
2	334 (RD/YE)	Window motor, feed
3	317 (GY/OG)	Window switch, feed, right rear, Up
4	170 (RD/LB)	Window lockout, switched power, output
		*Voltage in Run or Accessory (overload protected)
5	316 (YE/LB)	Window switch, feed, right rear, Down
6	333 (YE/RD)	Window motor, feed
7	–	not used
8	–	not used

C802

14A005

Speaker, right rear (18808)



F02069

Pin	Circuit	Circuit function
1	802 (OG/RD)	Speaker, right rear (18808) +
2	803 (BN/PK)	Speaker, right rear (18808) –

C803

14A005

Power window motor, right rear (23394)



F02387

Pin	Circuit	Circuit function
1	333 (YE/RD)	Window motor, feed, +/_
2	334 (RD/YE)	Window motor, feed, +/–

C805

14A005

Door lock unit, right rear

Early production



F02227

Pin	Circuit	Circuit function
1	117 (PK/BK)	Door lock, +/–
2	118 (PK/OG)	Door unlock, +/–

Late production



F02383

Pin	Circuit	Circuit function
1	118 (PK/OG)	Door unlock, +/–
2	117 (PK/BK)	Door lock, +/–