C4015 (WH)

13A409

Y234
Parking aid speaker



F02233

Pin	Circuit	Circuit function
1	1437 (BK/PK)	Parking aid speaker +
2	1438 (DG)	Parking aid speaker –

C4016

13A409

E109
Reversing lamp, right (13411)



F03099

Pin	Circuit	Circuit function
1	1205 (BK)	Ground
2	–	not used
3	140 (BK/PK)	Voltage supplied in reverse

C4017

13B431

E105
Reversing lamp, left (13411)



F03099

Pin	Circuit	Circuit function
1	1205 (BK)	Ground
2	–	not used
3	140 (BK/PK)	Voltage supplied in reverse

C4021

14A488

K355
Trailer tow relay, battery charge



F05129

Pin	Circuit	Circuit function
87	49 (OG)	Trailer tow relay, battery charge, output
87A	–	not used
85	1205 (BK)	Ground
86	1003 (GY/YE)	Voltage supplied in Start and Run (overload protected)
30	175 (BK/YE)	Voltage supplied at all times (overload protected)

C4022

14A488

K356
Trailer tow relay, parking lamp



F05129

Pin	Circuit	Circuit function
87	962 (BN/WH)	Trailer tow relay, switched output
87A	–	not used
85	14 (BN)	Power, Exterior lamps
86	1205 (BK)	Ground
30	1043 (DG/YE)	Voltage supplied at all times (overload protected)