C320 (GN)

14K024

N120
Light switch



F15001

Pin	Circuit	Circuit function
1	–	not used
2	30S-DA37 (RD/YE)	Voltage supplied at all times (not overload protected), Switched
	30S-DD37 (RD/YE)	Voltage supplied at all times (not overload protected), Switched
3	29S-LH4 (OG/BU)	Voltage supplied at all times (overload protected), Switched
4	29S-LE2 (OG/BU)	Voltage supplied at all times (overload protected), Switched
5	–	not used
6	29S-LD2 (OG/BU)	Voltage supplied at all times (overload protected), Switched
7	–	not used
8	29S-LD10 (OG/GN)	Voltage supplied at all times (overload protected), Switched

Pin	Circuit	Circuit function
9	–	not used
10	29S-LD1 (OG/YE)	Voltage supplied at all times (overload protected), Switched
11	29-LE21 (OG/BK)	Voltage supplied at all times (overload protected)
12	29S-LE4 (OG/BU) + 29S-LE6 (OG/YE)	Voltage supplied at all times (overload protected), Switched
	29S-LE4 (OG/YE)	Voltage supplied at all times (overload protected), Switched
13	30S-DD38 (RD/BU)	Voltage supplied at all times (not overload protected), Switched
14	30S-DD40 (RD/GN)	Voltage supplied at all times (not overload protected), Switched
15	30-LE21 (RD)	Voltage supplied at all times (not overload protected)