C1007

14290

Fog lamp relay



F05064

Pin	Circuit	Circuit function
1	30-LD8B (RD)	Voltage supplied at all times (overload protected)
2	31S-LD9 (BK/GN)	Fog lamp relay, control
3	30-LD8A (RD)	Voltage supplied at all times (overload protected)
4	–	not used
5	30S-LD2 (RD/BU)	Fog lamp relay, switched power, output

C1008

14290

A/C clutch relay



F05064

Pin	Circuit	Circuit function
1	15S-FA79 (GN/RD)	Voltage supplied in Start and Run (overload protected)
2	91S-FA79 (BN/BU)	A/C clutch relay, control
3	30-FA79 (RD/OG)	Voltage supplied at all times (overload protected)
4	–	not used
5	15S-FA6 (GN/YE)	A/C clutch relay, switched power, output

C1010

14300



F01215

14305



F01217

Pin	Circuit	Circuit function
1	30-BB10 (RD)	Battery cable +