Multifunction Switch, Lamp Portion (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
High beam	2 and 3	High beam	Closed circuit
		Flash–to–pass	Open circuit
		Low beam	Open circuit
Flash–to–pass	5 and 7	High beam	Open circuit
		Flash–to–pass	Closed circuit
		Low beam	Open circuit