C906

14334

E31
Vanity mirror lamp, right



F02117

Pin	Circuit	Circuit Function
1	31-LB23 (BK)	Ground
2	29S-LB23 (OG/WH)	Voltage supplied at all times (overload protected), Switched

C907

14334

E30
Vanity mirror lamp, left



F02117

Pin	Circuit	Circuit Function
1	31-LB16 (BK)	Ground
2	29S-LB16 (OG/GN)	Voltage supplied at all times (overload protected), Switched

C908a

14334

E113
Map reading lamp, left front

F01017

Pin	Circuit	Circuit Function
1	29S-LB12 (OG/YE)	Voltage supplied at all times (overload protected), Switched

C908b

14334

E113
Map reading lamp, left front

F01017

Pin	Circuit	Circuit Function
1	31S-LB12 (BK/YE)	Ground, Switched

C910

14334

N441
Map reading lamp switch, left front



F06179

Pin	Circuit	Circuit Function
1	31S-LB12 (BK/YE)	Ground, Switched
2	–	not used
3	–	not used
4	31-LB13 (BK)	Ground
5	–	not used
6	9-LB13 (BN/RD)	Sensor signal return (reference/ground)

C911

14334

A222
Auto–dimming interior mirror unit



F07075

Pin	Circuit	Circuit Function
1	20-AD15 (PK)	Voltage, hot in run only
2	31-AD15 (BK)	Ground
3	8-AD15 (WH/BU)	Sensor signal
4	–	not used
5	–	not used
6	–	not used
7	–	not used