Component Testing – Multifunction Switch, Lamp Portion (continued)

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch will Indicate
High Beam	5 and 2	High Beam	Closed Circuit
		Flash-to-Pass	Open Circuit
		Low Beam	Open Circuit
Low Beam/Flash-to-Pass	3 and 2	High Beam	Open Circuit
		Flash-to-Pass	Closed Circuit
		Low Beam	Closed Circuit
	5 and 7	High Beam	Open Circuit
		Flash-to-Pass	Closed Circuit
		Low Beam	Open Circuit