Exterior rear view mirror switch (17B676) (continued) As of 08/01

Component testing procedure

Circuit to test	Connect self–powered test light or ohm-meter to terminals	Move switch to these positions	A good switch will indicate
Left mirror		**Selector switch Left**	
Up	7 and 10 2 and 3	Up	Closed circuit
Down	7 and 3 2 and 10	Down	Closed circuit
Left	7 and 4 2 and 3	Left	Closed circuit
Right	7 and 3 2 and 4	Right	Closed circuit
Right mirror		**Selector switch Right**	
Up	7 and 9 2 and 3	Up	Closed circuit
Down	7 and 3 2 and 9	Down	Closed circuit
Left	7 and 5 2 and 3	Left	Closed circuit
Right	7 and 3 2 and 5	Right	Closed circuit
Folding Mirrors		**Selector switch In / Out**	
Power mirror fold in	7 and 1 2 and 6	In	Closed circuit
Power mirror fold out	7 and 6 2 and 1	Out	Closed circuit