## Light switch -4

### Component testing procedure

| Circuit to test | Connect self–powered test light or ohmmeter to terminals | Move switch to these positions | A good switch will indicate |
|---|---|---|---|
| **Headlamp circuit** | 8 and 6 | Off | Open circuit |
| | | Park | Open circuit |
| | | Low beam | Closed circuit |
| **Headlamp circuit (DRL)** | 8 and 4 | Off | Closed circuit |
| | | Park | Closed circuit |
| | | Low beam | Open circuit |
| **License plate lamps** | 11 and 16 | Off | Open circuit |
| | | Park | Closed circuit |
| | | Low beam | Closed circuit |
| **Parking Lamps** | 11 and 13 | Off | Open circuit |
| | | Park | Closed circuit |
| | | Low beam | Closed circuit |
| **Fog lamps** | 7 and 3 | Off | Open circuit |
| | | Fog lamps | Closed circuit |