## Multifunction Switch, Turn Portion (continued)

### Component testing procedure

| Circuit to test | Connect self–powered test light or ohmmeter to terminals | Move switch to these positions | A good switch will indicate |
|---|---|---|---|
| **Turn signal** | 1 and 8 | Left turn | Closed circuit |
| | 1 and 10 | Left turn | Closed circuit |
| | 1 and 5 | Right turn | Closed circuit |
| | 1 and 2 | Right turn | Closed circuit |
| **Hazard** | 4 and 8 | Turn signal switch in neutral, Hazard On | Closed circuit |
| | 4 and 5 | | |
| | 4 and 10 | | |
| | 4 and 2 | | |
| | 4 and 8 | Turn signal switch in neutral, Hazard Off | Open circuit |
| | 4 and 5 | | |
| | 4 and 10 | | |
| | 4 and 2 | | |
| | 9 and 10 | Turn signal switch in neutral, Hazard Off | Closed circuit |
| | 9 and 2 | | |