C403a

14A005

Cellular phone module



F12105

Pin	Circuit	Circuit function
1	1884 (OG)	VEMS Receive audio from PSE
2	–	not used
3	694 (BK/LG)	Ground
4	828 (VT/LB)	Voltage supplied at all times (overload protected)
5	964 (DB/LG)	Voltage in Run or Accessory (overload protected)
6	1883 (LB)	VEMS Transmit audio to PSE
7	713 (WH)	Transmit audio, Shield
8	714 (VT)	Transmit audio
9	828 (VT/LB)	Voltage supplied at all times (overload protected)
10	694 (BK/LG)	Ground
11	1881 (RD)	VEMS Serial communication interface transmit data to PSE
12	–	not used

C403b

14A005

Cellular phone module



F16097

Pin	Circuit	Circuit function
1	1271 (VT)	Cellular telephone charger
2	710 (LB)	External battery +
3	48	Shield
4	723 (GY/RD)	Cellular phone, wake up
5	1880 (WH)	VEMS Serial communication interface receive data from PSE
6	1882 (LG)	VEMS status mode
7	–	not used
8	48	Shield
9	832 (LB/PK)	Audio corporate protocol A
10	833 (TN)	Audio corporate protocol B
11	1272 (WH)	Cellular Telephone, Hook switch
12	718 (BK)	Handset, logic ground
13	1885 (BK)	VEMS Audio ground from PSE
14	724 (LB/YE)	Radio (18806), to cellular phone, audio –
15	725 (PK)	Radio (18806), to cellular phone, audio +
16	48	Shield