C1168 (BK)

12A581



F04263

19B573



F04251

(1) 348 (VT)
(2) 57 (BK)
(3) 321 (GY/WH)
(4) 439 (TN/LG)

C1171

13K027

Daytime Running Lamps (DRL) relay 1



Pin	Circuit	Circuit function
1	15 (RD/YE)	Power, Hot with Headlamps on
2	57 (BK)	Ground
3	175 (BK/YE)	Voltage in Run (overload protected)
4	1032 (WH/BK)	switched output
5	–	not used

C1170

12A581
13K027

Park brake relay



F05139

Pin	Circuit	Circuit function
1	295 (LB/PK)	Voltage in Run (overload protected)
2	162 (LG/RD)	Parking brake switch (15A851)
3	295 (LB/PK)	Voltage in Run (overload protected)
4	175 (BK/YE)	switched output
5	–	not used

C1172

12A581
13K027

Daytime Running Lamps (DRL) relay 2



F05129

Pin	Circuit	Circuit function
30	13 (RD/BK)	Headlamp circuit (DRL)
85	1032 (WH/BK)	Coil, feed
86	57 (BK)	Ground
	57 (BK)	Ground
87	471 (OG/LG)	Dropping resistor
87A	1033 (RD/YE)	Switched power