Master window control switch (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Left rear window circuit	7 and 1	Up	Closed circuit
	7 and 2	Down	Closed circuit
Right rear window circuit	7 and 5	Up	Closed circuit
	7 and 4	Down	Closed circuit
Window/lock switch bias output	7 and 3	Lock	Closed circuit
		Rest	Open circuit
One–Touch Down Switch	7 and 1	Down	480 Ω
Power and Ground Checks Before Any Other Tests	7 and 6	All switches – all positions	Open circuit
	6 all others, except 3	All switches – at rest	Closed circuit
Left front window circuit	7 and 4	Up	Closed circuit
	7 and 5	Down	Closed circuit
Right front window circuit	7 and 7	Up	Closed circuit
	7 and 6	Down	Closed circuit