COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Directional Control Switch to These Positions	A Good Switch Will Indicate
Right Mirror (Mirror Selector Switch Right)	1 and 6, 3 and 5	Left	Closed Circuit
	1 and 3, 5 and 6	Right	Closed Circuit
	1 and 8, 5 and 6	Up	Closed Circuit
	1 and 6, 5 and 8	Down	Closed Circuit

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Directional Control Switch to These Positions	A Good Switch Will Indicate
Left Mirror (Mirror Selector Switch Left)	1 and 6, 4 and 5	Left	Closed Circuit
	1 and 4, 5 and 6	Right	Closed Circuit
	1 and 7, 5 and 6	Up	Closed Circuit
	1 and 6, 5 and 7	Down	Closed Circuit