Multifunction Switch, Lamp Portion (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Turn signal	6 and 8	Left turn	Closed circuit
	6 and 10	Off	Open circuit
	6 and 5	Right turn	Closed circuit
	6 and 2	Off	Open circuit
Hazard	4 and 11	Turn signal switch in neutral, Hazard On	Closed circuit
	6 and 8		
	6 and 5		
	6 and 10		
	6 and 2		
	1 and 11	Turn signal switch in neutral, Hazard On	Open circuit
	9 and 10		
	9 and 2		
	4 and 11	Turn signal switch in neutral, Hazard Off	Open circuit
	1 and 11	Turn signal switch in neutral, Hazard Off	Closed circuit
	9 and 10		
	9 and 2		