C1011

14290

Blower motor relay



F05129

Pin	Circuit	Circuit function
30	181 (BN/OG)	Voltage supplied at all times (overload protected)
85	181 (BN/OG)	Voltage supplied at all times (overload protected)
86	364 (BK/LG)	Blower motor relay, control
87	371 (PK/WH)	Blower motor relay, switched output
87A	–	not used

C1016

14290

PCM power relay



F05110

Pin	Circuit	Circuit function
1	570 (BK/WH)	Ground
2	546 (DG/YE)	Voltage supplied in Start and Run (overload protected)
3	554 (YE/BK)	Voltage supplied at all times (overload protected)
4	–	not used
5	68 (OG/BK)	PCM power relay, switched output