Exterior rear view mirror switch (17B676) (continued)

Component testing procedure

Circuit to test		Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Left mirror	**Up**	1 and 7 5 and 6	Up	Closed circuit
	Down	1 and 6 5 and 7	Down	Closed circuit
	Left	1 and 4 5 and 6	Left	Closed circuit
	Right	1 and 6 5 and 4	Right	Closed circuit
Right mirror	**Up**	1 and 8 5 and 6	Up	Closed circuit
	Down	1 and 6 5 and 8	Down	Closed circuit
	Left	1 and 3 5 and 6	Left	Closed circuit
	Right	1 and 6 5 and 3	Right	Closed circuit