C149

14290

Brake booster sensor



F06173

Pin	Circuit	Circuit function
1	8-CF51 (WH/GN)	Brake booster sensor, Open
2	10-CF51 (GY/OG)	Brake booster sensor, closed
3	9-CF68 (BN/RD)	Brake booster sensor, Solenoid, feed
4	8-CF68 (WH/RD)	Brake booster sensor, Solenoid, return
5	9-CF51 (BN/GN)	Brake booster sensor, signal
6	–	not used

C150

14290

Wheel speed sensor, left front (2C205)



F02085

Pin	Circuit	Circuit function
1	7-CF32 (YE)	Wheel speed sensor, left front (2C205) +
2	8-CF32 (WH)	Wheel speed sensor, left front (2C205) -

C152

14290

Fog lamp, left front (15200)



F02037

Pin	Circuit	Circuit function
1	31-LD11 (BK/WH)	Ground
2	30S-LD11 (RD/WH)	Fog lamp relay, switched power, output