C1346

14398

Brake pedal relay



F05110

Pin	Circuit	Circuit function
1	602 (RD/LG)	Brake pedal relay, control
2	10 (LG/RD)	Voltage supplied at all times (overload protected)
3	10 (LG/RD)	Voltage supplied at all times (overload protected)
4	–	not used
5	511 (LG)	Switched power to stoplamps

C1348 (BK)

14398

Windshield wiper motor (17508)



F12179

Pin	Circuit	Circuit function
1	684 (PK/YE)	Wiper motor relay, high/low, input
2	–	not used
3	1203 (BK/LB)	logic ground
4	679 (GY/BK)	Vehicle Speed Sensor (VSS) +
5	950 (WH/BK)	Voltage supplied at all times (overload protected)
6	1205 (BK)	Ground
7	941 (BK/WH)	Windshield washer pump motor (17618), feed
8	1002 (BK/PK)	Voltage in Run or Accessory (overload protected)
9	671 (LB)	Wiper switch circuit
10	682 (DB)	Wiper switch circuit
11	680 (LB/OG)	Wiper switch circuit
12	1300 (VT)	Washer switch circuit