Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Power and Ground Checks Before Any Other Tests	7 and 6	All window switches, all positions	Open circuit
	6 and 4, 5, 2, 1, 7, 6, 5, 4	All window switches, at rest	Closed circuit
Left front window circuit	7 and 4	Down	Closed circuit
	7 and 5	Up	Closed circuit
Right front window circuit	7 and 1	Up	Closed circuit
	7 and 2	Down	Closed circuit
Left rear window circuit	7 and 2	Up	Closed circuit
	7 and 6	Down	Closed circuit
Right rear window circuit	7 and 5	Up	Closed circuit
	7 and 4	Down	Closed circuit
Window lockout	7 and 3	Window lockout, closed	Closed circuit
		Window lockout, Open	Open circuit
Automatic, switch	7 and 3	Automatic, switch, On	Closed circuit
		Automatic, switch, at rest	Open circuit