Power seat switch, 8–way power seat (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Lumbar circuit	2 and 10	Rest	Open circuit
		inflate	Closed circuit
		deflate	Open circuit
	1 and 10	Rest	Open circuit
		inflate	Open circuit
		deflate	Closed circuit
	2 and 9	Rest	Closed circuit
		inflate	Open circuit
		deflate	Closed circuit
	1 and 9	Rest	Closed circuit
		inflate	Closed circuit
		deflate	Open circuit
Forward/Rearward circuit	6 and 10	Rest	Open circuit
		inflate	Open circuit
		deflate	Closed circuit
	5 and 10	Rest	Open circuit
		inflate	Closed circuit
		deflate	Open circuit
	6 and 9	Rest	Closed circuit
		inflate	Closed circuit
		deflate	Open circuit
	5 and 9	Rest	Closed circuit
		inflate	Open circuit
		deflate	Closed circuit
Height circuit	4 and 10	Rest	Open circuit
		Up	Open circuit
		Down	Closed circuit
	3 and 10	Rest	Open circuit
		Up	Closed circuit
		Down	Open circuit
	4 and 9	Rest	Closed circuit
		Up	Closed circuit
		Down	Open circuit
	3 and 9	Rest	Closed circuit
		Up	Open circuit
		Down	Closed circuit