-6

Multifunction switch

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Headlamp Flasher	6 and 7	Neutral	Open Circuit
		Headlamp flasher	Closed Circuit
		High beam	Closed Circuit
High Beam	6 and 7	Neutral	Open Circuit
		Headlamp flasher	Closed Circuit
		High beam	Closed Circuit
High Beam	8 and 7	Neutral	Open Circuit
		Headlamp flasher	Open Circuit
		High beam	Closed Circuit
Low Beam	8 and 9	Neutral	Closed Circuit
		Headlamp flasher	Closed Circuit
		High beam	Open Circuit
LH Turn Signal	2 and 1	Neutral	Open Circuit
		Flash left (no detent)	Closed Circuit
		LH Turn signal	Closed Circuit
RH Turn Signal	2 and 3	Neutral	Open Circuit
		Flash right (no detent)	Closed Circuit
		RH Turn signal	Closed Circuit
Buzzer	4 and 5		40-50 Ohms