CONVERTIBLE

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self Powered test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Left Front Window Circuit	15 and 8	Up	Closed Circuit
	15 and 6	Down	Closed Circuit
Right Front Window Circuit	15 and 7	Up	Closed Circuit
	15 and 9	Down	Closed Circuit
Left Rear Window Circuit	15 and 10	Up	Closed Circuit
	15 and 12	Down	Closed Circuit
Right Rear Window Circuit	15 and 11	Up	Closed Circuit
	15 and 13	Down	Closed Circuit
Window Lock Switch	15 and 16	Window Lock Switch Towards Door	Closed Circuit
		Window Lock Switch Away From Door	Open Circuit
Door Lock Switch	3 and 4	Lock	Closed Circuit
	3 and 2	Unlock	Closed Circuit