Power seat switch, left – Expedition (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Front up/down circuit	7 and 2	Up	Closed circuit
		Rest	Open circuit
		Down	
	7 and 8	Up	Open circuit
		Rest	
		Down	Closed circuit
	1 and 2	Up	Open circuit
		Rest	Closed circuit
		Down	
	1 and 8	Up	Closed circuit
		Rest	
		Down	Open circuit
Rear up/down circuit	7 and 6	Up	Closed circuit
		Rest	Open circuit
		Down	
	7 and 4	Up	Open circuit
		Rest	
		Down	Closed circuit
	1 and 6	Up	Open circuit
		Rest	Closed circuit
		Down	
	1 and 4	Up	Closed circuit
		Rest	
		Down	Open circuit
Seat up/down circuit	7 and 2 7 and 6	Up	Closed circuit
		Rest	Open circuit
		Down	
	7 and 4 7 and 8	Up	Open circuit
		Rest	
		Down	Closed circuit
	1 and 2 1 and 6	Up	Open circuit
		Rest	Closed circuit
		Down	
	1 and 4 1 and 8	Up	Closed circuit
		Rest	
		Down	Open circuit