Door lock switch, driver side (14028) / Door lock switch, passenger side (14028)

Schematic



N204
Door lock switch, driver side (14028)
3) Lock
4) Unlock

N205
Door lock switch, passenger side (14028)
3) Lock
4) Unlock

Terminals

C505/C605



Component testing procedure

Circuit to test	Connect self–powered test light or ohm-meter to terminals	Move switch to these positions	A good switch will indicate
Lock Switch Circuit	6 and 1	Lock	Closed circuit
		Rest	Open circuit
Unlock Switch Circuit	6 and 5	Unlock	Closed circuit
		Rest	Open circuit