C290 (WH)

14N104

N10
Rear window defrost switch



F06155

Pin	Circuit	Circuit Function
1	IJ94 (PK/BK)	Illumination, Ground
2	HF15 (BK)	Ground
3	IJ04 (PK)	Illumination, feed
4	HF01 (GN/RD)	Rear window defrost switch, input
5	HF03 (GN)	Rear window defrost relay, switched output
6	HFE1 (BK)	Ground

C291

14N104

V12
ABS Diode



F02181

Pin	Circuit	Circuit Function
1	BS29 (WH/BK)	Anti–lock brake indicator, control
2	BS31 (PK)	Anti–lock brake indicator, control

C292 (WH)

14N104

N49
Hazard flasher switch



F10047

Pin	Circuit	Circuit Function
1	–	not used
2	–	not used
3	IJ93 (PK/BK)	Illumination, Ground
4	IJ03 (PK)	Illumination, feed
5	LB01 (PK/BU)	Voltage supplied in Start and Run (overload protected)
6	LB03 (OG)	Hazard flasher switch, switch sense
7	LB02 (GN/YE)	Voltage supplied at all times (overload protected)
8	LB17 (RD/WH)	Turn lamps, Right, switched power
9	LB04 (VT)	Turn Signal and Hazard Lamps, switched power
10	LB18 (RD/GN)	Turn lamps, Left, switched power

C293 (BK)

14A664

N54
Horn switch



F02157

Pin	Circuit	Circuit Function
1	(LB/BK)	Horn relay, control
2	(WH)	Ground