C319

13K702

R42
Cigar lighter, front



F03163

Pin	Circuit	Circuit Function
1	29-HA6 (RD)	Voltage supplied at all times (overload protected)
2	31-HA6 (BK)	Ground
3	–	not used

C323

14A005

A225
Driver safety belt retractor pretensioner



F03035

Pin	Circuit	Circuit Function
1	31S-JA33 (BK/BU)	Ground, Switched
2	–	not used
3	30S-JA33 (RD/BU)	Voltage supplied at all times (not overload protected), Switched

C322

14401

Y215
Brake shift interlock



F02071

Pin	Circuit	Circuit Function
1	31-TA33 (BK)	Ground
2	7S-TA33 (YE/VT)	Voltage D.C. supplied at all times (sensor), Switched

C324

14A005

B219
Cellular phone antenna



F01043

C325

14A005

A151
Antenna



F01047