C440

9L468

Wheel speed sensor, left rear



F02085

Pin	Circuit	Circuit function
1	8-CF34 (WH/BU)	Wheel speed sensor, left rear -
2	7-CF34 (YE/BU)	Wheel speed sensor, left rear +

C441

14A005

SSP 1 relay



F05129

Pin	Circuit	Circuit function
30	30-DG52 (RD/BU)	Voltage supplied at all times (overload protected)
85	31S-DG51 (BK/YE)	SSP 1 relay, control
86	30-DG51 (RD/YE)	Voltage supplied at all times (overload protected)
87	30-DD3 (RD/OG)	SSP 1 relay, switched power, output
87A	–	not used

C442

14A005

SSP 2 relay



F05129

Pin	Circuit	Circuit function
30	30-DG54 (RD/GN)	Voltage supplied at all times (overload protected)
85	31S-DG53 (BK/OG)	SSP 2 relay, control
86	30-DG53 (RD/OG)	Voltage supplied at all times (overload protected)
87	30-DD2 (RD/BU)	SSP 2 relay, switched power, output
87A	–	not used