Exterior rear view mirror switch (17B676)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Left mirror		Selector switch Left	
Up	6 and 3 3 and 1	Up	Closed circuit
Down	6 and 1 4 and 3	Down	Closed circuit
Left	6 and 3 4 and 7	Left	Closed circuit
Right	6 and 7 4 and 3	Right	Closed circuit
Right mirror		Selector switch Right	
Up	6 and 3 4 and 2	Up	Closed circuit
Down	6 and 2 4 and 3	Down	Closed circuit
Left	6 and 3 4 and 5	Left	Closed circuit
Right	6 and 5 4 and 3	Right	Closed circuit