Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Power and Ground Checks Before Any Other Tests	3 and 1	Power seats, Switches, all positions	Open circuit
	1 and 8, 6, 5, 2, 7, 4	Power seats, Switches, at rest	Closed circuit
Entire seat circuit	3 and 5	Forward	Closed circuit
	3 and 2	Rearward	Closed circuit
	3 and 6, 4	Down	Closed circuit
	3 and 8, 7	Up	Closed circuit
Front height circuit	3 and 6	Down	Closed circuit
	3 and 8	Up	Closed circuit
Rear height circuit	3 and 4	Down	Closed circuit
	3 and 7	Up	Closed circuit