-16

Power Window Switch

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Left Mirror Up/Down	4 and 2	Rest	Open Circuit
		Up	Closed Circuit
		Down	Open Circuit
	2 and 6	Rest	Open Circuit
		Up	Open Circuit
		Down	Closed Circuit
Right Mirror Up/Down	1 and 4	Rest	Open Circuit
		Up	Closed Circuit
		Down	Open Circuit
	1 and 6	Rest	Open Circuit
		Up	Open Circuit
		Down	Closed Circuit
Left Mirror Left/Right	5 and 4	Rest	Open Circuit
		Left	Open Circuit
		Right	Closed Circuit
	5 and 6	Rest	Open Circuit
		Left	Closed Circuit
		Right	Open Circuit
Right Mirror Left/Right	7 and 4	Rest	Open Circuit
		Left	Open Circuit
		Right	Closed Circuit
	7 and 6	Rest	Open Circuit
		Left	Closed Circuit
		Right	Open Circuit
Up/Down	4 and 3	Rest	Open Circuit
		Up	Open Circuit
		Down	Closed Circuit
	3 and 6	Rest	Open Circuit
		Up	Closed Circuit
		Down	Open Circuit
Left/Right	4 and 3	Rest	Open Circuit
		Left	Closed Circuit
		Right	Open Circuit
	3 and 6	Rest	Open Circuit
		Left	Open Circuit
		Right	Closed Circuit