C228 (BU)

14N104

K306
Power window relay



F04129

Pin	Circuit	Circuit function
1	PD02 (LG)	Voltage supplied at all times (overload protected)
2	PD04 (BK/RD)	Power window relay, control
3	PD03 (OG/BK)	Power window relay, switched output
4	–	not used
5	PD01 (LG)	Voltage supplied at all times (overload protected)

C230

14N104

K304
Front blower motor relay



F06127

C231

14N104

K1
Rear window defrost relay



F06127

C232

14N104

K306
Power window relay



F06127

C233

14N104

K41
Ignition relay



F04129

C234

14N104

K307
Tail lamp relay



F04129