C445

14A005

SSP 4 relay



F05129

Pin	Circuit	Circuit function
30	30-DG58 (RD/BU)	Voltage supplied in Start and Run (overload protected)
85	31S-DG57 (BK/YE)	SSP 4 relay, control
86	30-DG57 (RD/YE)	Voltage supplied in Start and Run (overload protected)
87	30S-DB16 (RD/GN)	SSP 4 relay, switched power, output
87A	–	not used

C446

14A005

Fuel pump relay



F05110

Pin	Circuit	Circuit function
1	31-RH5 (BK/BU)	Ground
2	15-RH5 (GN/BU)	Inertia Fuel Shutoff (IFS) switch (9D362), switched power, output
3	30-RH5 (RD/BU)	Voltage supplied at all times (overload protected)
4	–	not used
5	15S-DK32A (GN/RD)	Fuel pump relay, switched power, output

C449

14A005

Fuel pump motor diode



F02009

Pin	Circuit	Circuit function
1	15-RP12A (GN/WH)	Inertia Fuel Shutoff (IFS) switch (9D362), switched power, output
2	15-RH5 (GN/BU)	Inertia Fuel Shutoff (IFS) switch (9D362), switched power, output