**COMPONENT TESTING PROCEDURE**

| TO TEST | Connect Self-Powered Test Light or Ohmmeter to Terminals | Move Switch to These Positions | A Good Switch Will Indicate |
|---|---|---|---|
| **Power and Ground Checks Before Any Other Tests** | 4 and 5 | All Four Window Switches (all positions) | Open Circuit |
| | 5 and 1<br>5 and 2<br>5 and 1<br>5 and 2 | All Four Window Switches (at rest) | Closed Circuit |
| **Left Front Window Circuit** | 4 and 1 | Up | Closed Circuit |
| | 4 and 2 | Down | Closed Circuit |
| **Right Front Window Circuit** | 4 and 2 | Down | Closed Circuit |
| | 4 and 1 | Up | Closed Circuit |