C906b

14334

E31
Vanity mirror lamp,
right (04100)

F01006

Pin	Circuit	Circuit function
1	57 (BK)	Ground

C907a

14334

E30
Vanity mirror lamp,
left (04100)

F01006

Pin	Circuit	Circuit function
1	705 (LG.OG)	Battery saver relay, switched power

C907b

14334

E30
Vanity mirror lamp,
left (04100)

F01006

Pin	Circuit	Circuit function
1	57 (BK)	Ground

C908

14334

E113
Map reading lamp,
left front (13466)



F04351

Pin	Circuit	Circuit function
1	53 (BK/LB)	Interior lamp relay, switched power, output
2	57 (BK)	Ground
3	705 (LB/OG)	Battery saver relay, switched power
4	14 (BN)	Power, Exterior lamps

C909

14A005

A279
Electronic Compass
(19A548)



F04145

Pin	Circuit	Circuit function
1	702 (WH/BK)	Compass data +
2	703 (WH/OG)	Compass data –
3	964 (DB/LG)	fused feed, Accessory
4	57 (BK)	Ground