Power mirror adjust switch -18

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Power mirror, left **Up/down**	6 and 3	Rest	Open circuit
		Up	Closed circuit
		Down	Open circuit
	6 and 1	Rest	Open circuit
		Up	Open circuit
		Down	Closed circuit
Power mirror, right side **Up/down**	6 and 3	Rest	Open circuit
		Up	Closed circuit
		Down	Open circuit
	6 and 2	Rest	Open circuit
		Up	Open circuit
		Down	Closed circuit
Power mirror, left **Left/right**	6 and 3	Rest	Open circuit
		Left	Closed circuit
		Right	Open circuit
	6 and 7	Rest	Open circuit
		Left	Open circuit
		Right	Closed circuit
Power mirror, right side **Left/right**	6 and 5	Rest	Open circuit
		Left	Open circuit
		Right	Closed circuit
	6 and 3	Rest	Open circuit
		Left	Closed circuit
		Right	Open circuit
Up/down	4 and 3	Rest	Open circuit
		Up	Open circuit
		Down	Closed circuit
	3 and 6	Rest	Open circuit
		Up	Closed circuit
		Down	Open circuit
Left/right	4 and 3	Rest	Open circuit
		Left	Open circuit
		Right	Closed circuit
	3 and 6	Rest	Open circuit
		Left	Closed circuit
		Right	Open circuit