Power seat switch, left – Navigator (continued)

Component testing procedure

Circuit to test	Connect self–powered test light or ohmmeter to terminals	Move switch to these positions	A good switch will indicate
Forward/rearward circuit	F and E	Forward	Closed circuit
		Rest	Open circuit
		Rearward	
	F and D	Forward	Open circuit
		Rest	
		Rearward	Closed circuit
	C and E	Forward	Open circuit
		Rest	Closed circuit
		Rearward	
	C and D	Forward	Closed circuit
		Rest	
		Rearward	Open circuit
Front up/down circuit	F and M	Up	Closed circuit
		Rest	Open circuit
		Down	
	F and L	Up	Open circuit
		Rest	
		Down	Closed circuit
	C and M	Up	Open circuit
		Rest	Closed circuit
		Down	
	C and L	Up	Closed circuit
		Rest	
		Down	Open circuit