COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Right Mirror (Directional Control Switch Right)	1 and 3	Left	Closed Circuit
	5 and 6	Left	Closed Circuit
	1 and 6	Right	Closed Circuit
	5 and 3	Right	Closed Circuit
	1 and 8	Up	Closed Circuit
	5 and 6	Up	Closed Circuit
	1 and 6	Down	Closed Circuit
	5 and 8	Down	Closed Circuit

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Left Mirror (Directional Control Switch Left)	1 and 4	Left	Closed Circuit
	5 and 6	Left	Closed Circuit
	1 and 6	Right	Closed Circuit
	5 and 4	Right	Closed Circuit
	1 and 7	Up	Closed Circuit
	5 and 6	Up	Closed Circuit
	1 and 6	Down	Closed Circuit
	5 and 7	Down	Closed Circuit